

iBOX Series

Model	iHP1226	iHP1264	iHP1266	iHP1294	iHP1296	iHP1299	iHP1526	iHP1544	iHP1564	iHP1566	iHP1594	iHP1596	iHP1599	iHP3564	iHP3594	i2W8Mon	i2W8PA	i112S	i212S	i215LVS	iLF218
HP Resp (Type,dB/Oct)	BW24	BW24dB	BW24dB	BW24dB	BW24dB	BW24dB	BW24	BW24dB	BW24dB	BW24dB	BW24dB	BW24dB	BW24dB	BW24dB	BW24dB	BW24dB	BW24dB	BW48dB	BW24dB	BW24dB	BW24dB
HP Frequency (Hz)	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	50Hz	50Hz	65Hz	65Hz	30Hz	35Hz	35Hz	25Hz
HP Polarity (Norm/Inv)	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm	Norm
LP Resp (Type,dB/Oct)																		BW24dB	LR24dB	LR24dB	BW24dB
LP Frequency (Hz)																		100Hz	90	90	90Hz
Filter 1 Type	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ
Filter 1 Freq. (Hz)	5800	243	243	243	243	217	750	230	230	230	230	230	230	761	640	183	183	66	74	80	35
Filter 1 Oct-BW	0.2	0.16	0.8	0.16	0.16	0.88	1	0.24	0.24	0.24	0.24	0.24	0.24	0.21	0.32	0.45	0.45	0.5	0.3	0.2	0.33
Filter 1 Level (dB)	-3	-3	-3	-3	-3	-3	-3	-4	-4	-2	-4	-4	-4	-6	-7.5	-6	-4.5	2.5	-7	-4	5
Filter 2 Type	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ
Filter 2 Freq. (Hz)	3600	330	330	330	570	1643	4500	500	500	500	500	500	500	1035	1035	581	581	51	129	129	169
Filter 2 Oct-BW	0.2	0.33	0.37	0.33	0.51	0.18	0.2	0.33	0.33	0.33	0.33	0.33	0.33	0.19	0.19	0.5	0.5	0.27	-3.5	1	0.5
Filter 2 Level (dB)	-4	-3	-3	-3	-5	-3	-6	-5	-5	-5	-5	-5	-5	-3	-3	-5	-5	2	0.22	-6	-10
Filter 3 Type	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ
Filter 3 Freq. (Hz)	1650	1118	444	905	1015	330	15000	640	640	640	640	640	640	1612	1612	1409	1140	162	183	269	581
Filter 3 Oct-BW	0.25	0.33	0.5	0.33	0.33	0.61	0.6	0.33	0.33	0.33	0.33	0.33	0.33	0.17	0.17	0.49	0.33	1	1.01	-4	0.33
Filter 3 Level (dB)	-3	-3	-4	-3	-5	-2	-6	-4	-4	-4	-4	-4	-4	-4	-4	-4	-4	2.5	-2.5	-8	0.5
Filter 4 Type	PEQ	PEQ	PEQ	PEQ	PEQ		PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ
Filter 4 Freq. (Hz)	15000	1917	2114	2111	2325		2700	1.7K	1436	1800	1356	1356	1250	2071	2660	3620	1917	315	213	411	
Filter 4 Oct-BW	0.6	0.33	0.8	0.33	0.5		0.3	0.28	0.33	0.4	0.36	0.18	0.25	0.24	0.33	0.44	0.17	0.38	0.3	0.2	
Filter 4 Level (dB)	-6	1.5	-2.5	3	4		-2	-7	-3.5	-5	-4	-4	-6	-3	-3	-7	-4	-7.5	-4	-3	
Filter 5 Type					PEQ			PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ		
Filter 5 Freq. (Hz)					4474			2.2K	2660	4100	2660	2660	3700	2986	3551	6576	2511	529			
Filter 5 Oct-BW					0.5			0.2	0.33	0.4	0.33	0.33	0.33	0.25	0.57	0.54	0.2	0.25			
Filter 5 Level (dB)					-3			4	3	-6	-2	3	-4	3	-4	-7	3	-3.8			
Filter 6 Type														PEQ	PEQ	PEQ	PEQ	PEQ			
Filter 6 Freq. (Hz)														403	8446	3103	6967	1030			
Filter 6 Oct-BW														0.39	0.33	0.33	0.53	1			
Filter 6 Level (dB)														-6	-4	-1.5	-8	-5.75			
Filter 7 Type														PEQ	PEQ		PEQ				
Filter 7 Freq. (Hz)														627	403		3225				
Filter 7 Oct-BW														0.41	0.39		0.3				
Filter 7 Level (dB)														2	-6		-7.25				